


AUVA LED

Park and Street Luminaires



Images for the product family and options:



Description:

Pole-mounted LED street luminaire
 Light distribution: direct
 Optical system: lenses, tempered glass diffuser, impact resistant
 Housing: aluminium
 Colour: light grey, RAL7035

General data:

Mains voltage: 220-240V, 50-60Hz
 LED lifetime, h: 100000/L90B10
 SDCM: 3
 Protection class IEC: I (II optional)
 Ingress protection code: IP66
 Mechanical impact resistance: IK09
 Operating temperature range, °C: ta -40...+40 (J001-J012 ta -25...+40)

Installation:


With two screws on Ø60mm horizontal or vertical pole, on the wall (mounting bracket to be ordered separately). Adjustable installation angles: on horizontal pole: +/- 15 degrees, on vertical pole: +/- 15 degrees. Screw terminal, 3x1x2.5mm²

Environment:

Outdoor

Application:

Parking area, public space, street



Photocell PCA switches lighting fixtures ON or OFF, at the same time it can be mounted into IP protected light fitting serving as a standalone solution. The built-in photo-sensor records the brightness of the surroundings and switches the connected lighting fixtures on at dusk and of again at dawn. Technical data: IP65- dust and waterproof, 35 lux, 1:05 ratio. For more information see the option list.

Product	Length, mm	Width, mm	Height, mm	Luminaire output ¹ , lm	System power ² , W	System efficacy ³ , lm/W	CRI	CCT ⁴ , K	Weight, kg
Auva LED1x1900 J001 T730 LSM1	525	205	102	1840	12,5	147	70+	3000	3,5
Auva LED1x2250 J002 T730 LSM1	525	205	102	2172	15,1	144	70+	3000	3,5
Auva LED1x2600 J003 T730 LSM1	525	205	102	2514	17,2	146	70+	3000	3,5
Auva LED1x2900 J004 T730 LSM1	525	205	102	2818	19,8	142	70+	3000	3,5
Auva LED1x3250 J005 T730 LSM1	525	205	102	3140	22,2	141	70+	3000	3,5
Auva LED1x3700 J006 T730 LSM1	525	205	102	3106	26,1	119	70+	3000	3,5
Auva LED1x3800 J007 T730 LSM1	525	205	102	3680	23,9	154	70+	3000	3,5
Auva LED1x4500 J008 T730 LSM1	525	205	102	4345	28,9	150	70+	3000	3,5
Auva LED1x5200 J009 T730 LSM1	525	205	102	5028	33,6	150	70+	3000	3,5
Auva LED1x5800 J010 T730 LSM1	525	205	102	5635	38,7	146	70+	3000	3,5
Auva LED1x6450 J011 T730 LSM1	525	205	102	6279	43,9	143	70+	3000	3,5
Auva LED1x7350 J012 T730 LSM1	525	205	102	6212	51,7	120	70+	3000	3,5
Auva LED1x5700 J013 T730 LSM1	525	250	102	5520	35,8	154	70+	3000	4,9
Auva LED1x6700 J014 T730 LSM1	525	250	102	6517	43,3	151	70+	3000	4,9
Auva LED1x7750 J015 T730 LSM1	525	250	102	7542	51,0	148	70+	3000	4,9
Auva LED1x8700 J016 T730 LSM1	525	250	102	8453	58,6	144	70+	3000	5
Auva LED1x9700 J017 T730 LSM1	525	250	102	9419	66,5	142	70+	3000	5
Auva LED1x11050 J018 T730 LSM1	525	250	102	9317	78,3	119	70+	3000	5
Auva LED1x7600 J019 T730 LSM1	625	288	102	7360	48,3	152	70+	3000	7,2
Auva LED1x8950 J020 T730 LSM1	625	288	102	8689	57,7	151	70+	3000	7,2
Auva LED1x10350 J021 T730 LSM1	625	288	102	10056	68,0	148	70+	3000	7,3
Auva LED1x11600 J022 T730 LSM1	625	288	102	11271	77,3	146	70+	3000	7,3
Auva LED1x12900 J023 T730 LSM1	625	288	102	12559	87,7	143	70+	3000	7,3
Auva LED1x14700 J024 T730 LSM1	625	288	102	14283	103,3	138	70+	3000	7,3
Auva LED1x11400 J025 T730 LSM1	625	288	102	11040	71,6	154	70+	3000	7,2
Auva LED1x13400 J026 T730 LSM1	625	288	102	13034	86,6	151	70+	3000	7,3
Auva LED1x15500 J027 T730 LSM1	625	288	102	15085	100,9	150	70+	3000	7,3
Auva LED1x17400 J028 T730 LSM1	625	288	102	16906	116,0	146	70+	3000	7,3
Auva LED1x19350 J029 T730 LSM1	625	288	102	18838	131,6	143	70+	3000	7,3
Auva LED1x15200 J031 T730 LSM1	776	320	102	14721	94,5	156	70+	3000	9,4
Auva LED1x17900 J032 T730 LSM1	776	320	102	17379	114,2	152	70+	3000	9,4
Auva LED1x20700 J033 T730 LSM1	776	320	102	20113	134,5	150	70+	3000	9,4
Auva LED1x23150 J034 T730 LSM1	776	320	102	22541	154,7	146	70+	3000	9,4
Auva LED1x25800 J035 T730 LSM1	776	320	102	25118	175,5	143	70+	3000	9,4
Auva LED1x1900 J001 T740 LSM1	525	205	102	1897	12,5	152	70+	4000	3,5
Auva LED1x2250 J002 T740 LSM1	525	205	102	2233	15,1	148	70+	4000	3,5
Auva LED1x2600 J003 T740 LSM1	525	205	102	2582	17,2	150	70+	4000	3,5
Auva LED1x2900 J004 T740 LSM1	525	205	102	2892	19,8	146	70+	4000	3,5
Auva LED1x3250 J005 T740 LSM1	525	205	102	3223	22,2	145	70+	4000	3,5
Auva LED1x3700 J006 T740 LSM1	525	205	102	3667	26,1	140	70+	4000	3,5
Auva LED1x3800 J007 T740 LSM1	525	205	102	3793	23,9	159	70+	4000	3,5
Auva LED1x4500 J008 T740 LSM1	525	205	102	4466	28,9	155	70+	4000	3,5
Auva LED1x5200 J009 T740 LSM1	525	205	102	5163	33,6	154	70+	4000	3,5
Auva LED1x5800 J010 T740 LSM1	525	205	102	5785	38,7	149	70+	4000	3,5
Auva LED1x6450 J011 T740 LSM1	525	205	102	6446	43,9	147	70+	4000	3,5
Auva LED1x7350 J012 T740 LSM1	525	205	102	7335	51,7	142	70+	4000	3,5
Auva LED1x5700 J013 T740 LSM1	525	250	102	5690	35,8	159	70+	4000	4,9
Auva LED1x6700 J014 T740 LSM1	525	250	102	6700	43,3	155	70+	4000	4,9
Auva LED1x7750 J015 T740 LSM1	525	250	102	7745	51,0	152	70+	4000	4,9
Auva LED1x8700 J016 T740 LSM1	525	250	102	8677	58,6	148	70+	4000	5
Auva LED1x9700 J017 T740 LSM1	525	250	102	9669	66,5	145	70+	4000	5
Auva LED1x11050 J018 T740 LSM1	525	250	102	11002	78,3	141	70+	4000	5
Auva LED1x7600 J019 T740 LSM1	625	288	102	7586	48,3	157	70+	4000	7,2
Auva LED1x8950 J020 T740 LSM1	625	288	102	8933	57,7	155	70+	4000	7,2
Auva LED1x10350 J021 T740 LSM1	625	288	102	10327	68,0	152	70+	4000	7,3
Auva LED1x11600 J022 T740 LSM1	625	288	102	11569	77,3	150	70+	4000	7,3
Auva LED1x12900 J023 T740 LSM1	625	288	102	12892	87,7	147	70+	4000	7,3
Auva LED1x14700 J024 T740 LSM1	625	288	102	14669	103,3	142	70+	4000	7,3
Auva LED1x11400 J025 T740 LSM1	625	288	102	11379	71,6	159	70+	4000	7,2
Auva LED1x13400 J026 T740 LSM1	625	288	102	13399	86,6	155	70+	4000	7,3
Auva LED1x15500 J027 T740 LSM1	625	288	102	15490	100,9	154	70+	4000	7,3
Auva LED1x17400 J028 T740 LSM1	625	288	102	17354	116,0	150	70+	4000	7,3
Auva LED1x19350 J029 T740 LSM1	625	288	102	19338	131,6	147	70+	4000	7,3
Auva LED1x15200 J031 T740 LSM1	776	320	102	15173	94,5	161	70+	4000	9,4
Auva LED1x17900 J032 T740 LSM1	776	320	102	17866	114,2	156	70+	4000	9,4
Auva LED1x20700 J033 T740 LSM1	776	320	102	20653	134,5	154	70+	4000	9,4
Auva LED1x23150 J034 T740 LSM1	776	320	102	23138	154,7	150	70+	4000	9,4
Auva LED1x25800 J035 T740 LSM1	776	320	102	25784	175,5	147	70+	4000	9,4
Auva LED1x1900 J001 T730 LSM2	525	205	102	1882	12,5	151	70+	3000	3,5
Auva LED1x2250 J002 T730 LSM2	525	205	102	2222	15,1	147	70+	3000	3,5
Auva LED1x2600 J003 T730 LSM2	525	205	102	2572	17,2	150	70+	3000	3,5
Auva LED1x2900 J004 T730 LSM2	525	205	102	2882	19,8	146	70+	3000	3,5
Auva LED1x3250 J005 T730 LSM2	525	205	102	3212	22,2	145	70+	3000	3,5
Auva LED1x3700 J006 T730 LSM2	525	205	102	3177	26,1	122	70+	3000	3,5
Auva LED1x3800 J007 T730 LSM2	525	205	102	3765	23,9	158	70+	3000	3,5
Auva LED1x4500 J008 T730 LSM2	525	205	102	4445	28,9	154	70+	3000	3,5
Auva LED1x5200 J009 T730 LSM2	525	205	102	5144	33,6	153	70+	3000	3,5
Auva LED1x5800 J010 T730 LSM2	525	205	102	5765	38,7	149	70+	3000	3,5
Auva LED1x6450 J011 T730 LSM2	525	205	102	6424	43,9	146	70+	3000	3,5
Auva LED1x7350 J012 T730 LSM2	525	205	102	6354	51,7	123	70+	3000	3,5
Auva LED1x5700 J013 T730 LSM2	525	250	102	5647	35,8	158	70+	3000	4,9
Auva LED1x6700 J014 T730 LSM2	525	250	102	6667	43,3	154	70+	3000	4,9
Auva LED1x7750 J015 T730 LSM2	525	250	102	7716	51,0	151	70+	3000	4,9
Auva LED1x8700 J016 T730 LSM2	525	250	102	8647	58,6	148	70+	3000	5
Auva LED1x9700 J017 T730 LSM2	525	250	102	9636	66,5	145	70+	3000	5
Auva LED1x11050 J018 T730 LSM2	525	250	102	9532	78,3	122	70+	3000	5
Auva LED1x7600 J019 T730 LSM2	625	288	102	7530	48,3	156	70+	3000	7,2
Auva LED1x8950 J020 T730 LSM2	625	288	102	8889	57,7	154	70+	3000	7,2
Auva LED1x10350 J021 T730 LSM2	625	288	102	10288	68,0	151	70+	3000	7,3
Auva LED1x11600 J022 T730 LSM2	625	288	102	11530	77,3	149	70+	3000	7,3
Auva LED1x12900 J023 T730 LSM2	625	288	102	12848	87,7	146	70+	3000	7,3
Auva LED1x14700 J024 T730 LSM2	625	288	102	14611	103,3	141	70+	3000	7,3

Product	Length, mm	Width, mm	Height, mm	Luminaire output ¹ , lm	System power ² , W	System efficacy ³ , lm/W	CRI	CCT ⁴ , K	Weight, kg
Auva LED1x11400 J025 T730 LSM2	625	288	102	11294	71,6	158	70+	3000	7,2
Auva LED1x13400 J026 T730 LSM2	625	288	102	13334	86,6	154	70+	3000	7,3
Auva LED1x15500 J027 T730 LSM2	625	288	102	15431	100,9	153	70+	3000	7,3
Auva LED1x17400 J028 T730 LSM2	625	288	102	17295	116,0	149	70+	3000	7,3
Auva LED1x19350 J029 T730 LSM2	625	288	102	19271	131,6	146	70+	3000	7,3
Auva LED1x15200 J031 T730 LSM2	776	320	102	15059	94,5	159	70+	3000	9,4
Auva LED1x17900 J032 T730 LSM2	776	320	102	17778	114,2	156	70+	3000	9,4
Auva LED1x20700 J033 T730 LSM2	776	320	102	20575	134,5	153	70+	3000	9,4
Auva LED1x23150 J034 T730 LSM2	776	320	102	23060	154,7	149	70+	3000	9,4
Auva LED1x25800 J035 T730 LSM2	776	320	102	25695	175,5	146	70+	3000	9,4
Auva LED1x1900 J001 T740 LSM2	525	205	102	1940	12,5	155	70+	4000	3,5
Auva LED1x2250 J002 T740 LSM2	525	205	102	2285	15,1	151	70+	4000	3,5
Auva LED1x2600 J003 T740 LSM2	525	205	102	2641	17,2	154	70+	4000	3,5
Auva LED1x2900 J004 T740 LSM2	525	205	102	2959	19,8	149	70+	4000	3,5
Auva LED1x3250 J005 T740 LSM2	525	205	102	3297	22,2	149	70+	4000	3,5
Auva LED1x3700 J006 T740 LSM2	525	205	102	3752	26,1	144	70+	4000	3,5
Auva LED1x3800 J007 T740 LSM2	525	205	102	3880	23,9	162	70+	4000	3,5
Auva LED1x4500 J008 T740 LSM2	525	205	102	4569	28,9	158	70+	4000	3,5
Auva LED1x5200 J009 T740 LSM2	525	205	102	5282	33,6	157	70+	4000	3,5
Auva LED1x5800 J010 T740 LSM2	525	205	102	5918	38,7	153	70+	4000	3,5
Auva LED1x6450 J011 T740 LSM2	525	205	102	6594	43,9	150	70+	4000	3,5
Auva LED1x7350 J012 T740 LSM2	525	205	102	7503	51,7	145	70+	4000	3,5
Auva LED1x5700 J013 T740 LSM2	525	250	102	5820	35,8	163	70+	4000	4,9
Auva LED1x6700 J014 T740 LSM2	525	250	102	6854	43,3	158	70+	4000	4,9
Auva LED1x7750 J015 T740 LSM2	525	250	102	7923	51,0	155	70+	4000	4,9
Auva LED1x8700 J016 T740 LSM2	525	250	102	8876	58,6	151	70+	4000	5
Auva LED1x9700 J017 T740 LSM2	525	250	102	9891	66,5	149	70+	4000	5
Auva LED1x11050 J018 T740 LSM2	525	250	102	11255	78,3	144	70+	4000	5
Auva LED1x7600 J019 T740 LSM2	625	288	102	7761	48,3	161	70+	4000	7,2
Auva LED1x8950 J020 T740 LSM2	625	288	102	9138	57,7	158	70+	4000	7,2
Auva LED1x10350 J021 T740 LSM2	625	288	102	10564	68,0	155	70+	4000	7,3
Auva LED1x11600 J022 T740 LSM2	625	288	102	11835	77,3	153	70+	4000	7,3
Auva LED1x12900 J023 T740 LSM2	625	288	102	13189	87,7	150	70+	4000	7,3
Auva LED1x14700 J024 T740 LSM2	625	288	102	15007	103,3	145	70+	4000	7,3
Auva LED1x11400 J025 T740 LSM2	625	288	102	11641	71,6	163	70+	4000	7,2
Auva LED1x13400 J026 T740 LSM2	625	288	102	13707	86,6	158	70+	4000	7,3
Auva LED1x15500 J027 T740 LSM2	625	288	102	15846	100,9	157	70+	4000	7,3
Auva LED1x17400 J028 T740 LSM2	625	288	102	17753	116,0	153	70+	4000	7,3
Auva LED1x19350 J029 T740 LSM2	625	288	102	19783	131,6	150	70+	4000	7,3
Auva LED1x15200 J031 T740 LSM2	776	320	102	15521	94,5	164	70+	4000	9,4
Auva LED1x17900 J032 T740 LSM2	776	320	102	18277	114,2	160	70+	4000	9,4
Auva LED1x20700 J033 T740 LSM2	776	320	102	21128	134,5	157	70+	4000	9,4
Auva LED1x23150 J034 T740 LSM2	776	320	102	23670	154,7	153	70+	4000	9,4
Auva LED1x25800 J035 T740 LSM2	776	320	102	26377	175,5	150	70+	4000	9,4
Auva LED1x1900 J001 T730 LSS1	525	205	102	1840	12,5	147	70+	3000	3,5
Auva LED1x2250 J002 T730 LSS1	525	205	102	2172	15,1	144	70+	3000	3,5
Auva LED1x2600 J003 T730 LSS1	525	205	102	2514	17,2	146	70+	3000	3,5
Auva LED1x2900 J004 T730 LSS1	525	205	102	2818	19,8	142	70+	3000	3,5
Auva LED1x3250 J005 T730 LSS1	525	205	102	3140	22,2	141	70+	3000	3,5
Auva LED1x3700 J006 T730 LSS1	525	205	102	3106	26,1	119	70+	3000	3,5
Auva LED1x3800 J007 T730 LSS1	525	205	102	3680	23,9	154	70+	3000	3,5
Auva LED1x4500 J008 T730 LSS1	525	205	102	4345	28,9	150	70+	3000	3,5
Auva LED1x5200 J009 T730 LSS1	525	205	102	5028	33,6	150	70+	3000	3,5
Auva LED1x5800 J010 T730 LSS1	525	205	102	5635	38,7	146	70+	3000	3,5
Auva LED1x6450 J011 T730 LSS1	525	205	102	6279	43,9	143	70+	3000	3,5
Auva LED1x7350 J012 T730 LSS1	525	205	102	6212	51,7	120	70+	3000	3,5
Auva LED1x5700 J013 T730 LSS1	525	250	102	5520	35,8	154	70+	3000	4,9
Auva LED1x6700 J014 T730 LSS1	525	250	102	6517	43,3	151	70+	3000	4,9
Auva LED1x7750 J015 T730 LSS1	525	250	102	7542	51,0	148	70+	3000	4,9
Auva LED1x8700 J016 T730 LSS1	525	250	102	8453	58,6	144	70+	3000	5
Auva LED1x9700 J017 T730 LSS1	525	250	102	9419	66,5	142	70+	3000	5
Auva LED1x11050 J018 T730 LSS1	525	250	102	9317	78,3	119	70+	3000	5
Auva LED1x7600 J019 T730 LSS1	625	288	102	7360	48,3	152	70+	3000	7,2
Auva LED1x8950 J020 T730 LSS1	625	288	102	8689	57,7	151	70+	3000	7,2
Auva LED1x10350 J021 T730 LSS1	625	288	102	10056	68,0	148	70+	3000	7,3
Auva LED1x11600 J022 T730 LSS1	625	288	102	11271	77,3	146	70+	3000	7,3
Auva LED1x12900 J023 T730 LSS1	625	288	102	12559	87,7	143	70+	3000	7,3
Auva LED1x14700 J024 T730 LSS1	625	288	102	14283	103,3	138	70+	3000	7,3
Auva LED1x11400 J025 T730 LSS1	625	288	102	11040	71,6	154	70+	3000	7,2
Auva LED1x13400 J026 T730 LSS1	625	288	102	13034	86,6	151	70+	3000	7,3
Auva LED1x15500 J027 T730 LSS1	625	288	102	15085	100,9	150	70+	3000	7,3
Auva LED1x17400 J028 T730 LSS1	625	288	102	16906	116,0	146	70+	3000	7,3
Auva LED1x19350 J029 T730 LSS1	625	288	102	18838	131,6	143	70+	3000	7,3
Auva LED1x15200 J031 T730 LSS1	776	320	102	14721	94,5	156	70+	3000	9,4
Auva LED1x17900 J032 T730 LSS1	776	320	102	17379	114,2	152	70+	3000	9,4
Auva LED1x20700 J033 T730 LSS1	776	320	102	20113	134,5	150	70+	3000	9,4
Auva LED1x23150 J034 T730 LSS1	776	320	102	22541	154,7	146	70+	3000	9,4
Auva LED1x25800 J035 T730 LSS1	776	320	102	25118	175,5	143	70+	3000	9,4
Auva LED1x1900 J001 T740 LSS1	525	205	102	1897	12,5	152	70+	4000	3,5
Auva LED1x2250 J002 T740 LSS1	525	205	102	2233	15,1	148	70+	4000	3,5
Auva LED1x2600 J003 T740 LSS1	525	205	102	2582	17,2	150	70+	4000	3,5
Auva LED1x2900 J004 T740 LSS1	525	205	102	2892	19,8	146	70+	4000	3,5
Auva LED1x3250 J005 T740 LSS1	525	205	102	3223	22,2	145	70+	4000	3,5
Auva LED1x3700 J006 T740 LSS1	525	205	102	3667	26,1	140	70+	4000	3,5
Auva LED1x3800 J007 T740 LSS1	525	205	102	3793	23,9	159	70+	4000	3,5
Auva LED1x4500 J008 T740 LSS1	525	205	102	4466	28,9	155	70+	4000	3,5
Auva LED1x5200 J009 T740 LSS1	525	205	102	5163	33,6	154	70+	4000	3,5
Auva LED1x5800 J010 T740 LSS1	525	205	102	5785	38,7	149	70+	4000	3,5
Auva LED1x6450 J011 T740 LSS1	525	205	102	6446	43,9	147	70+	4000	3,5
Auva LED1x7350 J012 T740 LSS1	525	205	102	7335	51,7	142	70+	4000	3,5
Auva LED1x5700 J013 T740 LSS1	525	250	102	5690	35,8	159	70+	4000	4,9
Auva LED1x6700 J014 T740 LSS1	525	250	102	6700	43,3	155	70+	4000	4,9
Auva LED1x7750 J015 T740 LSS1	525	250	102	7745	51,0	152	70+	4000	4,9
Auva LED1x8700 J016 T740 LSS1	525	250	102	8677	58,6	148	70+	4000	5
Auva LED1x9700 J017 T740 LSS1	525	250	102	9669	66,5	145	70+	4000	5

Product	Length, mm	Width, mm	Height, mm	Luminaire output', lm	System power', W	System efficacy', lm/W	CRI	CCT', K	Weight, kg
Auva LED1x11050 J018 T740 LSS1	525	250	102	11002	78,3	141	70+	4000	5
Auva LED1x7600 J019 T740 LSS1	625	288	102	7586	48,3	157	70+	4000	7,2
Auva LED1x8950 J020 T740 LSS1	625	288	102	8933	57,7	155	70+	4000	7,2
Auva LED1x10350 J021 T740 LSS1	625	288	102	10327	68,0	152	70+	4000	7,3
Auva LED1x11600 J022 T740 LSS1	625	288	102	11569	77,3	150	70+	4000	7,3
Auva LED1x12900 J023 T740 LSS1	625	288	102	12892	87,7	147	70+	4000	7,3
Auva LED1x14700 J024 T740 LSS1	625	288	102	14669	103,3	142	70+	4000	7,3
Auva LED1x11400 J025 T740 LSS1	625	288	102	11379	71,6	159	70+	4000	7,2
Auva LED1x13400 J026 T740 LSS1	625	288	102	13399	86,6	155	70+	4000	7,3
Auva LED1x15500 J027 T740 LSS1	625	288	102	15490	100,9	154	70+	4000	7,3
Auva LED1x17400 J028 T740 LSS1	625	288	102	17354	116,0	150	70+	4000	7,3
Auva LED1x19350 J029 T740 LSS1	625	288	102	19338	131,6	147	70+	4000	7,3
Auva LED1x15200 J031 T740 LSS1	776	320	102	15173	94,5	161	70+	4000	9,4
Auva LED1x17900 J032 T740 LSS1	776	320	102	17866	114,2	156	70+	4000	9,4
Auva LED1x20700 J033 T740 LSS1	776	320	102	20653	134,5	154	70+	4000	9,4
Auva LED1x23150 J034 T740 LSS1	776	320	102	23138	154,7	150	70+	4000	9,4
Auva LED1x25800 J035 T740 LSS1	776	320	102	25784	175,5	147	70+	4000	9,4
Auva LED1x1900 J001 T730 LSS2	525	205	102	1861	12,5	149	70+	3000	3,5
Auva LED1x2250 J002 T730 LSS2	525	205	102	2197	15,1	145	70+	3000	3,5
Auva LED1x2600 J003 T730 LSS2	525	205	102	2543	17,2	148	70+	3000	3,5
Auva LED1x2900 J004 T730 LSS2	525	205	102	2850	19,8	144	70+	3000	3,5
Auva LED1x3250 J005 T730 LSS2	525	205	102	3176	22,2	143	70+	3000	3,5
Auva LED1x3700 J006 T730 LSS2	525	205	102	3142	26,1	120	70+	3000	3,5
Auva LED1x3800 J007 T730 LSS2	525	205	102	3722	23,9	156	70+	3000	3,5
Auva LED1x4500 J008 T730 LSS2	525	205	102	4395	28,9	152	70+	3000	3,5
Auva LED1x5200 J009 T730 LSS2	525	205	102	5086	33,6	151	70+	3000	3,5
Auva LED1x5800 J010 T730 LSS2	525	205	102	5700	38,7	147	70+	3000	3,5
Auva LED1x6450 J011 T730 LSS2	525	205	102	6352	43,9	145	70+	3000	3,5
Auva LED1x7350 J012 T730 LSS2	525	205	102	6283	51,7	122	70+	3000	3,5
Auva LED1x5700 J013 T730 LSS2	525	250	102	5584	35,8	156	70+	3000	4,9
Auva LED1x6700 J014 T730 LSS2	525	250	102	6592	43,3	152	70+	3000	4,9
Auva LED1x7750 J015 T730 LSS2	525	250	102	7629	51,0	150	70+	3000	4,9
Auva LED1x8700 J016 T730 LSS2	525	250	102	8550	58,6	146	70+	3000	5
Auva LED1x9700 J017 T730 LSS2	525	250	102	9527	66,5	143	70+	3000	5
Auva LED1x11050 J018 T730 LSS2	525	250	102	9425	78,3	120	70+	3000	5
Auva LED1x7600 J019 T730 LSS2	625	288	102	7445	48,3	154	70+	3000	7,2
Auva LED1x8950 J020 T730 LSS2	625	288	102	8789	57,7	152	70+	3000	7,2
Auva LED1x10350 J021 T730 LSS2	625	288	102	10172	68,0	150	70+	3000	7,3
Auva LED1x11600 J022 T730 LSS2	625	288	102	11400	77,3	147	70+	3000	7,3
Auva LED1x12900 J023 T730 LSS2	625	288	102	12703	87,7	145	70+	3000	7,3
Auva LED1x14700 J024 T730 LSS2	625	288	102	14447	103,3	140	70+	3000	7,3
Auva LED1x11400 J025 T730 LSS2	625	288	102	11167	71,6	156	70+	3000	7,2
Auva LED1x13400 J026 T730 LSS2	625	288	102	13184	86,6	152	70+	3000	7,3
Auva LED1x15500 J027 T730 LSS2	625	288	102	15258	100,9	151	70+	3000	7,3
Auva LED1x17400 J028 T730 LSS2	625	288	102	17100	116,0	147	70+	3000	7,3
Auva LED1x19350 J029 T730 LSS2	625	288	102	19055	131,6	145	70+	3000	7,3
Auva LED1x15200 J031 T730 LSS2	776	320	102	14890	94,5	158	70+	3000	9,4
Auva LED1x17900 J032 T730 LSS2	776	320	102	17578	114,2	154	70+	3000	9,4
Auva LED1x20700 J033 T730 LSS2	776	320	102	20344	134,5	151	70+	3000	9,4
Auva LED1x23150 J034 T730 LSS2	776	320	102	22800	154,7	147	70+	3000	9,4
Auva LED1x25800 J035 T730 LSS2	776	320	102	25406	175,5	145	70+	3000	9,4
Auva LED1x1900 J001 T740 LSS2	525	205	102	1918	12,5	153	70+	4000	3,5
Auva LED1x2250 J002 T740 LSS2	525	205	102	2259	15,1	150	70+	4000	3,5
Auva LED1x2600 J003 T740 LSS2	525	205	102	2611	17,2	152	70+	4000	3,5
Auva LED1x2900 J004 T740 LSS2	525	205	102	2926	19,8	148	70+	4000	3,5
Auva LED1x3250 J005 T740 LSS2	525	205	102	3260	22,2	147	70+	4000	3,5
Auva LED1x3700 J006 T740 LSS2	525	205	102	3710	26,1	142	70+	4000	3,5
Auva LED1x3800 J007 T740 LSS2	525	205	102	3837	23,9	161	70+	4000	3,5
Auva LED1x4500 J008 T740 LSS2	525	205	102	4518	28,9	156	70+	4000	3,5
Auva LED1x5200 J009 T740 LSS2	525	205	102	5223	33,6	155	70+	4000	3,5
Auva LED1x5800 J010 T740 LSS2	525	205	102	5851	38,7	151	70+	4000	3,5
Auva LED1x6450 J011 T740 LSS2	525	205	102	6520	43,9	149	70+	4000	3,5
Auva LED1x7350 J012 T740 LSS2	525	205	102	7419	51,7	144	70+	4000	3,5
Auva LED1x5700 J013 T740 LSS2	525	250	102	5755	35,8	161	70+	4000	4,9
Auva LED1x6700 J014 T740 LSS2	525	250	102	6777	43,3	157	70+	4000	4,9
Auva LED1x7750 J015 T740 LSS2	525	250	102	7834	51,0	154	70+	4000	4,9
Auva LED1x8700 J016 T740 LSS2	525	250	102	8777	58,6	150	70+	4000	5
Auva LED1x9700 J017 T740 LSS2	525	250	102	9780	66,5	147	70+	4000	5
Auva LED1x11050 J018 T740 LSS2	525	250	102	11129	78,3	142	70+	4000	5
Auva LED1x7600 J019 T740 LSS2	625	288	102	7673	48,3	159	70+	4000	7,2
Auva LED1x8950 J020 T740 LSS2	625	288	102	9036	57,7	157	70+	4000	7,2
Auva LED1x10350 J021 T740 LSS2	625	288	102	10445	68,0	154	70+	4000	7,3
Auva LED1x11600 J022 T740 LSS2	625	288	102	11702	77,3	151	70+	4000	7,3
Auva LED1x12900 J023 T740 LSS2	625	288	102	13040	87,7	149	70+	4000	7,3
Auva LED1x14700 J024 T740 LSS2	625	288	102	14838	103,3	144	70+	4000	7,3
Auva LED1x11400 J025 T740 LSS2	625	288	102	11510	71,6	161	70+	4000	7,2
Auva LED1x13400 J026 T740 LSS2	625	288	102	13553	86,6	157	70+	4000	7,3
Auva LED1x15500 J027 T740 LSS2	625	288	102	15668	100,9	155	70+	4000	7,3
Auva LED1x17400 J028 T740 LSS2	625	288	102	17553	116,0	151	70+	4000	7,3
Auva LED1x19350 J029 T740 LSS2	625	288	102	19560	131,6	149	70+	4000	7,3
Auva LED1x15200 J031 T740 LSS2	776	320	102	15347	94,5	162	70+	4000	9,4
Auva LED1x17900 J032 T740 LSS2	776	320	102	18071	114,2	158	70+	4000	9,4
Auva LED1x20700 J033 T740 LSS2	776	320	102	20890	134,5	155	70+	4000	9,4
Auva LED1x23150 J034 T740 LSS2	776	320	102	23404	154,7	151	70+	4000	9,4
Auva LED1x25800 J035 T740 LSS2	776	320	102	26081	175,5	149	70+	4000	9,4
Auva LED1x1900 J001 T730 LSPR	525	205	102	1861	12,5	149	70+	3000	3,5
Auva LED1x2250 J002 T730 LSPR	525	205	102	2197	15,1	145	70+	3000	3,5
Auva LED1x2600 J003 T730 LSPR	525	205	102	2543	17,2	148	70+	3000	3,5
Auva LED1x2900 J004 T730 LSPR	525	205	102	2850	19,8	144	70+	3000	3,5
Auva LED1x3250 J005 T730 LSPR	525	205	102	3176	22,2	143	70+	3000	3,5
Auva LED1x3700 J006 T730 LSPR	525	205	102	3142	26,1	120	70+	3000	3,5
Auva LED1x3800 J007 T730 LSPR	525	205	102	3722	23,9	156	70+	3000	3,5
Auva LED1x4500 J008 T730 LSPR	525	205	102	4395	28,9	152	70+	3000	3,5
Auva LED1x5200 J009 T730 LSPR	525	205	102	5086	33,6	151	70+	3000	3,5

Product	Length, mm	Width, mm	Height, mm	Luminaire output, lm	System power, W	System efficacy, lm/W	CRI	CCT, K	Weight, kg
Auva LED1x5800 J010 T730 LSPR	525	205	102	5700	38,7	147	70+	3000	3,5
Auva LED1x6450 J011 T730 LSPR	525	205	102	6352	43,9	145	70+	3000	3,5
Auva LED1x7350 J012 T730 LSPR	525	205	102	6283	51,7	122	70+	3000	3,5
Auva LED1x5700 J013 T730 LSPR	525	250	102	5584	35,8	156	70+	3000	4,9
Auva LED1x6700 J014 T730 LSPR	525	250	102	6592	43,3	152	70+	3000	4,9
Auva LED1x7750 J015 T730 LSPR	525	250	102	7629	51,0	150	70+	3000	4,9
Auva LED1x8700 J016 T730 LSPR	525	250	102	8550	58,6	146	70+	3000	5
Auva LED1x9700 J017 T730 LSPR	525	250	102	9527	66,5	143	70+	3000	5
Auva LED1x11050 J018 T730 LSPR	525	250	102	9425	78,3	120	70+	3000	5
Auva LED1x7600 J019 T730 LSPR	625	288	102	7445	48,3	154	70+	3000	7,2
Auva LED1x8950 J020 T730 LSPR	625	288	102	8789	57,7	152	70+	3000	7,2
Auva LED1x10350 J021 T730 LSPR	625	288	102	10172	68,0	150	70+	3000	7,3
Auva LED1x11600 J022 T730 LSPR	625	288	102	11400	77,3	147	70+	3000	7,3
Auva LED1x12900 J023 T730 LSPR	625	288	102	12703	87,7	145	70+	3000	7,3
Auva LED1x14700 J024 T730 LSPR	625	288	102	14447	103,3	140	70+	3000	7,3
Auva LED1x11400 J025 T730 LSPR	625	288	102	11167	71,6	156	70+	3000	7,2
Auva LED1x13400 J026 T730 LSPR	625	288	102	13184	86,6	152	70+	3000	7,3
Auva LED1x15500 J027 T730 LSPR	625	288	102	15258	100,9	151	70+	3000	7,3
Auva LED1x17400 J028 T730 LSPR	625	288	102	17100	116,0	147	70+	3000	7,3
Auva LED1x19350 J029 T730 LSPR	625	288	102	19055	131,6	145	70+	3000	7,3
Auva LED1x15200 J031 T730 LSPR	776	320	102	14890	94,5	158	70+	3000	9,4
Auva LED1x17900 J032 T730 LSPR	776	320	102	17578	114,2	154	70+	3000	9,4
Auva LED1x20700 J033 T730 LSPR	776	320	102	20344	134,5	151	70+	3000	9,4
Auva LED1x23150 J034 T730 LSPR	776	320	102	22800	154,7	147	70+	3000	9,4
Auva LED1x25800 J035 T730 LSPR	776	320	102	25406	175,5	145	70+	3000	9,4
Auva LED1x1900 J001 T740 LSPR	525	205	102	1918	12,5	153	70+	4000	3,5
Auva LED1x2250 J002 T740 LSPR	525	205	102	2259	15,1	150	70+	4000	3,5
Auva LED1x2600 J003 T740 LSPR	525	205	102	2611	17,2	152	70+	4000	3,5
Auva LED1x2900 J004 T740 LSPR	525	205	102	2926	19,8	148	70+	4000	3,5
Auva LED1x3250 J005 T740 LSPR	525	205	102	3260	22,2	147	70+	4000	3,5
Auva LED1x3700 J006 T740 LSPR	525	205	102	3710	26,1	142	70+	4000	3,5
Auva LED1x3800 J007 T740 LSPR	525	205	102	3837	23,9	161	70+	4000	3,5
Auva LED1x4500 J008 T740 LSPR	525	205	102	4518	28,9	156	70+	4000	3,5
Auva LED1x5200 J009 T740 LSPR	525	205	102	5223	33,6	155	70+	4000	3,5
Auva LED1x5800 J010 T740 LSPR	525	205	102	5851	38,7	151	70+	4000	3,5
Auva LED1x6450 J011 T740 LSPR	525	205	102	6520	43,9	149	70+	4000	3,5
Auva LED1x7350 J012 T740 LSPR	525	205	102	7419	51,7	144	70+	4000	3,5
Auva LED1x5700 J013 T740 LSPR	525	250	102	5755	35,8	161	70+	4000	4,9
Auva LED1x6700 J014 T740 LSPR	525	250	102	6777	43,3	157	70+	4000	4,9
Auva LED1x7750 J015 T740 LSPR	525	250	102	7834	51,0	154	70+	4000	4,9
Auva LED1x8700 J016 T740 LSPR	525	250	102	8777	58,6	150	70+	4000	5
Auva LED1x9700 J017 T740 LSPR	525	250	102	9780	66,5	147	70+	4000	5
Auva LED1x11050 J018 T740 LSPR	525	250	102	11129	78,3	142	70+	4000	5
Auva LED1x7600 J019 T740 LSPR	625	288	102	7673	48,3	159	70+	4000	7,2
Auva LED1x8950 J020 T740 LSPR	625	288	102	9036	57,7	157	70+	4000	7,2
Auva LED1x10350 J021 T740 LSPR	625	288	102	10445	68,0	154	70+	4000	7,3
Auva LED1x11600 J022 T740 LSPR	625	288	102	11702	77,3	151	70+	4000	7,3
Auva LED1x12900 J023 T740 LSPR	625	288	102	13040	87,7	149	70+	4000	7,3
Auva LED1x14700 J024 T740 LSPR	625	288	102	14838	103,3	144	70+	4000	7,3
Auva LED1x11400 J025 T740 LSPR	625	288	102	11510	71,6	161	70+	4000	7,2
Auva LED1x13400 J026 T740 LSPR	625	288	102	13553	86,6	157	70+	4000	7,3
Auva LED1x15500 J027 T740 LSPR	625	288	102	15668	100,9	155	70+	4000	7,3
Auva LED1x17400 J028 T740 LSPR	625	288	102	17553	116,0	151	70+	4000	7,3
Auva LED1x19350 J029 T740 LSPR	625	288	102	19560	131,6	149	70+	4000	7,3
Auva LED1x15200 J031 T740 LSPR	776	320	102	15347	94,5	162	70+	4000	9,4
Auva LED1x17900 J032 T740 LSPR	776	320	102	18071	114,2	158	70+	4000	9,4
Auva LED1x20700 J033 T740 LSPR	776	320	102	20890	134,5	155	70+	4000	9,4
Auva LED1x23150 J034 T740 LSPR	776	320	102	23404	154,7	151	70+	4000	9,4
Auva LED1x25800 J035 T740 LSPR	776	320	102	26081	175,5	149	70+	4000	9,4
Auva LED1x1900 J001 T730 LSPL	525	205	102	1861	12,5	149	70+	3000	3,5
Auva LED1x2250 J002 T730 LSPL	525	205	102	2197	15,1	145	70+	3000	3,5
Auva LED1x2600 J003 T730 LSPL	525	205	102	2543	17,2	148	70+	3000	3,5
Auva LED1x2900 J004 T730 LSPL	525	205	102	2850	19,8	144	70+	3000	3,5
Auva LED1x3250 J005 T730 LSPL	525	205	102	3176	22,2	143	70+	3000	3,5
Auva LED1x3700 J006 T730 LSPL	525	205	102	3142	26,1	120	70+	3000	3,5
Auva LED1x3800 J007 T730 LSPL	525	205	102	3722	23,9	156	70+	3000	3,5
Auva LED1x4500 J008 T730 LSPL	525	205	102	4395	28,9	152	70+	3000	3,5
Auva LED1x5200 J009 T730 LSPL	525	205	102	5086	33,6	151	70+	3000	3,5
Auva LED1x5800 J010 T730 LSPL	525	205	102	5700	38,7	147	70+	3000	3,5
Auva LED1x6450 J011 T730 LSPL	525	205	102	6352	43,9	145	70+	3000	3,5
Auva LED1x7350 J012 T730 LSPL	525	205	102	6283	51,7	122	70+	3000	3,5
Auva LED1x5700 J013 T730 LSPL	525	250	102	5584	35,8	156	70+	3000	4,9
Auva LED1x6700 J014 T730 LSPL	525	250	102	6592	43,3	152	70+	3000	4,9
Auva LED1x7750 J015 T730 LSPL	525	250	102	7629	51,0	150	70+	3000	4,9
Auva LED1x8700 J016 T730 LSPL	525	250	102	8550	58,6	146	70+	3000	5
Auva LED1x9700 J017 T730 LSPL	525	250	102	9527	66,5	143	70+	3000	5
Auva LED1x11050 J018 T730 LSPL	525	250	102	9425	78,3	120	70+	3000	5
Auva LED1x7600 J019 T730 LSPL	625	288	102	7445	48,3	154	70+	3000	7,2
Auva LED1x8950 J020 T730 LSPL	625	288	102	8789	57,7	152	70+	3000	7,2
Auva LED1x10350 J021 T730 LSPL	625	288	102	10172	68,0	150	70+	3000	7,3
Auva LED1x11600 J022 T730 LSPL	625	288	102	11400	77,3	147	70+	3000	7,3
Auva LED1x12900 J023 T730 LSPL	625	288	102	12703	87,7	145	70+	3000	7,3
Auva LED1x14700 J024 T730 LSPL	625	288	102	14447	103,3	140	70+	3000	7,3
Auva LED1x11400 J025 T730 LSPL	625	288	102	11167	71,6	156	70+	3000	7,2
Auva LED1x13400 J026 T730 LSPL	625	288	102	13184	86,6	152	70+	3000	7,3
Auva LED1x15500 J027 T730 LSPL	625	288	102	15258	100,9	151	70+	3000	7,3
Auva LED1x17400 J028 T730 LSPL	625	288	102	17100	116,0	147	70+	3000	7,3
Auva LED1x19350 J029 T730 LSPL	625	288	102	19055	131,6	145	70+	3000	7,3
Auva LED1x15200 J031 T730 LSPL	776	320	102	14890	94,5	158	70+	3000	9,4
Auva LED1x17900 J032 T730 LSPL	776	320	102	17578	114,2	154	70+	3000	9,4
Auva LED1x20700 J033 T730 LSPL	776	320	102	20344	134,5	151	70+	3000	9,4
Auva LED1x23150 J034 T730 LSPL	776	320	102	22800	154,7	147	70+	3000	9,4
Auva LED1x25800 J035 T730 LSPL	776	320	102	25406	175,5	145	70+	3000	9,4
Auva LED1x1900 J001 T740 LSPL	525	205	102	1918	12,5	153	70+	4000	3,5
Auva LED1x2250 J002 T740 LSPL	525	205	102	2259	15,1	150	70+	4000	3,5

Product	Length, mm	Width, mm	Height, mm	Luminaire output, lm	System power, W	System efficacy, lm/W	CRI	CCT, K	Weight, kg
Auva LED1x2600 J003 T740 LSPL	525	205	102	2611	17,2	152	70+	4000	3,5
Auva LED1x2900 J004 T740 LSPL	525	205	102	2926	19,8	148	70+	4000	3,5
Auva LED1x3250 J005 T740 LSPL	525	205	102	3260	22,2	147	70+	4000	3,5
Auva LED1x3700 J006 T740 LSPL	525	205	102	3710	26,1	142	70+	4000	3,5
Auva LED1x3800 J007 T740 LSPL	525	205	102	3837	23,9	161	70+	4000	3,5
Auva LED1x4500 J008 T740 LSPL	525	205	102	4518	28,9	156	70+	4000	3,5
Auva LED1x5200 J009 T740 LSPL	525	205	102	5223	33,6	155	70+	4000	3,5
Auva LED1x5800 J010 T740 LSPL	525	205	102	5851	38,7	151	70+	4000	3,5
Auva LED1x6450 J011 T740 LSPL	525	205	102	6520	43,9	149	70+	4000	3,5
Auva LED1x7350 J012 T740 LSPL	525	205	102	7419	51,7	144	70+	4000	3,5
Auva LED1x5700 J013 T740 LSPL	525	250	102	5755	35,8	161	70+	4000	4,9
Auva LED1x6700 J014 T740 LSPL	525	250	102	6777	43,3	157	70+	4000	4,9
Auva LED1x7750 J015 T740 LSPL	525	250	102	7834	51,0	154	70+	4000	4,9
Auva LED1x8700 J016 T740 LSPL	525	250	102	8777	58,6	150	70+	4000	5
Auva LED1x9700 J017 T740 LSPL	525	250	102	9780	66,5	147	70+	4000	5
Auva LED1x11050 J018 T740 LSPL	525	250	102	11129	78,3	142	70+	4000	5
Auva LED1x7600 J019 T740 LSPL	625	288	102	7673	48,3	159	70+	4000	7,2
Auva LED1x8950 J020 T740 LSPL	625	288	102	9036	57,7	157	70+	4000	7,2
Auva LED1x10350 J021 T740 LSPL	625	288	102	10445	68,0	154	70+	4000	7,3
Auva LED1x11600 J022 T740 LSPL	625	288	102	11702	77,3	151	70+	4000	7,3
Auva LED1x12900 J023 T740 LSPL	625	288	102	13040	87,7	149	70+	4000	7,3
Auva LED1x14700 J024 T740 LSPL	625	288	102	14838	103,3	144	70+	4000	7,3
Auva LED1x11400 J025 T740 LSPL	625	288	102	11510	71,6	161	70+	4000	7,2
Auva LED1x13400 J026 T740 LSPL	625	288	102	13553	86,6	157	70+	4000	7,3
Auva LED1x15500 J027 T740 LSPL	625	288	102	15668	100,9	155	70+	4000	7,3
Auva LED1x17400 J028 T740 LSPL	625	288	102	17553	116,0	151	70+	4000	7,3
Auva LED1x19350 J029 T740 LSPL	625	288	102	19560	131,6	149	70+	4000	7,3
Auva LED1x15200 J031 T740 LSPL	776	320	102	15347	94,5	162	70+	4000	9,4
Auva LED1x17900 J032 T740 LSPL	776	320	102	18071	114,2	158	70+	4000	9,4
Auva LED1x20700 J033 T740 LSPL	776	320	102	20890	134,5	155	70+	4000	9,4
Auva LED1x23150 J034 T740 LSPL	776	320	102	23404	154,7	151	70+	4000	9,4
Auva LED1x25800 J035 T740 LSPL	776	320	102	26081	175,5	149	70+	4000	9,4
Auva LED1x1900 J001 T730 LSA1	525	205	102	1777	12,5	142	70+	3000	3,5
Auva LED1x2250 J002 T730 LSA1	525	205	102	2097	15,1	139	70+	3000	3,5
Auva LED1x2600 J003 T730 LSA1	525	205	102	2427	17,2	141	70+	3000	3,5
Auva LED1x2900 J004 T730 LSA1	525	205	102	2721	19,8	137	70+	3000	3,5
Auva LED1x3250 J005 T730 LSA1	525	205	102	3031	22,2	137	70+	3000	3,5
Auva LED1x3700 J006 T730 LSA1	525	205	102	2999	26,1	115	70+	3000	3,5
Auva LED1x3800 J007 T730 LSA1	525	205	102	3553	23,9	149	70+	3000	3,5
Auva LED1x4500 J008 T730 LSA1	525	205	102	4195	28,9	145	70+	3000	3,5
Auva LED1x5200 J009 T730 LSA1	525	205	102	4855	33,6	144	70+	3000	3,5
Auva LED1x5800 J010 T730 LSA1	525	205	102	5441	38,7	141	70+	3000	3,5
Auva LED1x6450 J011 T730 LSA1	525	205	102	6063	43,9	138	70+	3000	3,5
Auva LED1x7350 J012 T730 LSA1	525	205	102	5997	51,7	116	70+	3000	3,5
Auva LED1x5700 J013 T730 LSA1	525	250	102	5330	35,8	149	70+	3000	4,9
Auva LED1x6700 J014 T730 LSA1	525	250	102	6292	43,3	145	70+	3000	4,9
Auva LED1x7750 J015 T730 LSA1	525	250	102	7282	51,0	143	70+	3000	4,9
Auva LED1x8700 J016 T730 LSA1	525	250	102	8162	58,6	139	70+	3000	5
Auva LED1x9700 J017 T730 LSA1	525	250	102	9094	66,5	137	70+	3000	5
Auva LED1x11050 J018 T730 LSA1	525	250	102	8996	78,3	115	70+	3000	5
Auva LED1x7600 J019 T730 LSA1	625	288	102	7107	48,3	147	70+	3000	7,2
Auva LED1x8950 J020 T730 LSA1	625	288	102	8390	57,7	145	70+	3000	7,2
Auva LED1x10350 J021 T730 LSA1	625	288	102	9710	68,0	143	70+	3000	7,3
Auva LED1x11600 J022 T730 LSA1	625	288	102	10882	77,3	141	70+	3000	7,3
Auva LED1x12900 J023 T730 LSA1	625	288	102	12126	87,7	138	70+	3000	7,3
Auva LED1x14700 J024 T730 LSA1	625	288	102	13791	103,3	134	70+	3000	7,3
Auva LED1x11400 J025 T730 LSA1	625	288	102	10660	71,6	149	70+	3000	7,2
Auva LED1x13400 J026 T730 LSA1	625	288	102	12584	86,6	145	70+	3000	7,3
Auva LED1x15500 J027 T730 LSA1	625	288	102	14564	100,9	144	70+	3000	7,3
Auva LED1x17400 J028 T730 LSA1	625	288	102	16323	116,0	141	70+	3000	7,3
Auva LED1x19350 J029 T730 LSA1	625	288	102	18189	131,6	138	70+	3000	7,3
Auva LED1x15200 J031 T730 LSA1	776	320	102	14213	94,5	150	70+	3000	9,4
Auva LED1x17900 J032 T730 LSA1	776	320	102	16779	114,2	147	70+	3000	9,4
Auva LED1x20700 J033 T730 LSA1	776	320	102	19419	134,5	144	70+	3000	9,4
Auva LED1x23150 J034 T730 LSA1	776	320	102	21764	154,7	141	70+	3000	9,4
Auva LED1x25800 J035 T730 LSA1	776	320	102	24252	175,5	138	70+	3000	9,4
Auva LED1x1900 J001 T740 LSA1	525	205	102	1831	12,5	146	70+	4000	3,5
Auva LED1x2250 J002 T740 LSA1	525	205	102	2156	15,1	143	70+	4000	3,5
Auva LED1x2600 J003 T740 LSA1	525	205	102	2493	17,2	145	70+	4000	3,5
Auva LED1x2900 J004 T740 LSA1	525	205	102	2793	19,8	141	70+	4000	3,5
Auva LED1x3250 J005 T740 LSA1	525	205	102	3112	22,2	140	70+	4000	3,5
Auva LED1x3700 J006 T740 LSA1	525	205	102	3541	26,1	136	70+	4000	3,5
Auva LED1x3800 J007 T740 LSA1	525	205	102	3662	23,9	153	70+	4000	3,5
Auva LED1x4500 J008 T740 LSA1	525	205	102	4312	28,9	149	70+	4000	3,5
Auva LED1x5200 J009 T740 LSA1	525	205	102	4985	33,6	148	70+	4000	3,5
Auva LED1x5800 J010 T740 LSA1	525	205	102	5585	38,7	144	70+	4000	3,5
Auva LED1x6450 J011 T740 LSA1	525	205	102	6224	43,9	142	70+	4000	3,5
Auva LED1x7350 J012 T740 LSA1	525	205	102	7082	51,7	137	70+	4000	3,5
Auva LED1x5700 J013 T740 LSA1	525	250	102	5493	35,8	153	70+	4000	4,9
Auva LED1x6700 J014 T740 LSA1	525	250	102	6469	43,3	149	70+	4000	4,9
Auva LED1x7750 J015 T740 LSA1	525	250	102	7478	51,0	147	70+	4000	4,9
Auva LED1x8700 J016 T740 LSA1	525	250	102	8378	58,6	143	70+	4000	5
Auva LED1x9700 J017 T740 LSA1	525	250	102	9336	66,5	140	70+	4000	5
Auva LED1x11050 J018 T740 LSA1	525	250	102	10623	78,3	136	70+	4000	5
Auva LED1x7600 J019 T740 LSA1	625	288	102	7325	48,3	152	70+	4000	7,2
Auva LED1x8950 J020 T740 LSA1	625	288	102	8625	57,7	149	70+	4000	7,2
Auva LED1x10350 J021 T740 LSA1	625	288	102	9970	68,0	147	70+	4000	7,3
Auva LED1x11600 J022 T740 LSA1	625	288	102	11170	77,3	145	70+	4000	7,3
Auva LED1x12900 J023 T740 LSA1	625	288	102	12448	87,7	142	70+	4000	7,3
Auva LED1x14700 J024 T740 LSA1	625	288	102	14164	103,3	137	70+	4000	7,3
Auva LED1x11400 J025 T740 LSA1	625	288	102	10987	71,6	153	70+	4000	7,2
Auva LED1x13400 J026 T740 LSA1	625	288	102	12937	86,6	149	70+	4000	7,3
Auva LED1x15500 J027 T740 LSA1	625	288	102	14956	100,9	148	70+	4000	7,3
Auva LED1x17400 J028 T740 LSA1	625	288	102	16755	116,0	144	70+	4000	7,3
Auva LED1x19350 J029 T740 LSA1	625	288	102	18671	131,6	142	70+	4000	7,3

Product	Length, mm	Width, mm	Height, mm	Luminaire output, lm	System power, W	System efficacy, lm/W	CRI	CCT, K	Weight, kg
Auva LED1x15200 J031 T740 LSA1	776	320	102	14649	94,5	155	70+	4000	9,4
Auva LED1x17900 J032 T740 LSA1	776	320	102	17250	114,2	151	70+	4000	9,4
Auva LED1x20700 J033 T740 LSA1	776	320	102	19941	134,5	148	70+	4000	9,4
Auva LED1x23150 J034 T740 LSA1	776	320	102	22340	154,7	144	70+	4000	9,4
Auva LED1x25800 J035 T740 LSA1	776	320	102	24895	175,5	142	70+	4000	9,4
Auva LED1x1900 J001 T730 LSA2	525	205	102	1777	12,5	142	70+	3000	3,5
Auva LED1x2250 J002 T730 LSA2	525	205	102	2097	15,1	139	70+	3000	3,5
Auva LED1x2600 J003 T730 LSA2	525	205	102	2427	17,2	141	70+	3000	3,5
Auva LED1x2900 J004 T730 LSA2	525	205	102	2721	19,8	137	70+	3000	3,5
Auva LED1x3250 J005 T730 LSA2	525	205	102	3031	22,2	137	70+	3000	3,5
Auva LED1x3700 J006 T730 LSA2	525	205	102	2999	26,1	115	70+	3000	3,5
Auva LED1x3800 J007 T730 LSA2	525	205	102	3553	23,9	149	70+	3000	3,5
Auva LED1x4500 J008 T730 LSA2	525	205	102	4195	28,9	145	70+	3000	3,5
Auva LED1x5200 J009 T730 LSA2	525	205	102	4855	33,6	144	70+	3000	3,5
Auva LED1x5800 J010 T730 LSA2	525	205	102	5441	38,7	141	70+	3000	3,5
Auva LED1x6450 J011 T730 LSA2	525	205	102	6063	43,9	138	70+	3000	3,5
Auva LED1x7350 J012 T730 LSA2	525	205	102	5997	51,7	116	70+	3000	3,5
Auva LED1x5700 J013 T730 LSA2	525	250	102	5330	35,8	149	70+	3000	4,9
Auva LED1x6700 J014 T730 LSA2	525	250	102	6292	43,3	145	70+	3000	4,9
Auva LED1x7750 J015 T730 LSA2	525	250	102	7282	51,0	143	70+	3000	4,9
Auva LED1x8700 J016 T730 LSA2	525	250	102	8162	58,6	139	70+	3000	5
Auva LED1x9700 J017 T730 LSA2	525	250	102	9094	66,5	137	70+	3000	5
Auva LED1x11050 J018 T730 LSA2	525	250	102	8996	78,3	115	70+	3000	5
Auva LED1x7600 J019 T730 LSA2	625	288	102	7107	48,3	147	70+	3000	7,2
Auva LED1x8950 J020 T730 LSA2	625	288	102	8390	57,7	145	70+	3000	7,2
Auva LED1x10350 J021 T730 LSA2	625	288	102	9710	68,0	143	70+	3000	7,3
Auva LED1x11600 J022 T730 LSA2	625	288	102	10882	77,3	141	70+	3000	7,3
Auva LED1x12900 J023 T730 LSA2	625	288	102	12126	87,7	138	70+	3000	7,3
Auva LED1x14700 J024 T730 LSA2	625	288	102	13791	103,3	134	70+	3000	7,3
Auva LED1x11400 J025 T730 LSA2	625	288	102	10660	71,6	149	70+	3000	7,2
Auva LED1x13400 J026 T730 LSA2	625	288	102	12584	86,6	145	70+	3000	7,3
Auva LED1x15500 J027 T730 LSA2	625	288	102	14564	100,9	144	70+	3000	7,3
Auva LED1x17400 J028 T730 LSA2	625	288	102	16323	116,0	141	70+	3000	7,3
Auva LED1x19350 J029 T730 LSA2	625	288	102	18189	131,6	138	70+	3000	7,3
Auva LED1x15200 J031 T730 LSA2	776	320	102	14213	94,5	150	70+	3000	9,4
Auva LED1x17900 J032 T730 LSA2	776	320	102	16779	114,2	147	70+	3000	9,4
Auva LED1x20700 J033 T730 LSA2	776	320	102	19419	134,5	144	70+	3000	9,4
Auva LED1x23150 J034 T730 LSA2	776	320	102	21764	154,7	141	70+	3000	9,4
Auva LED1x25800 J035 T730 LSA2	776	320	102	24252	175,5	138	70+	3000	9,4
Auva LED1x1900 J001 T740 LSA2	525	205	102	1831	12,5	146	70+	4000	3,5
Auva LED1x2250 J002 T740 LSA2	525	205	102	2156	15,1	143	70+	4000	3,5
Auva LED1x2600 J003 T740 LSA2	525	205	102	2493	17,2	145	70+	4000	3,5
Auva LED1x2900 J004 T740 LSA2	525	205	102	2793	19,8	141	70+	4000	3,5
Auva LED1x3250 J005 T740 LSA2	525	205	102	3112	22,2	140	70+	4000	3,5
Auva LED1x3700 J006 T740 LSA2	525	205	102	3541	26,1	136	70+	4000	3,5
Auva LED1x3800 J007 T740 LSA2	525	205	102	3662	23,9	153	70+	4000	3,5
Auva LED1x4500 J008 T740 LSA2	525	205	102	4312	28,9	149	70+	4000	3,5
Auva LED1x5200 J009 T740 LSA2	525	205	102	4985	33,6	148	70+	4000	3,5
Auva LED1x5800 J010 T740 LSA2	525	205	102	5585	38,7	144	70+	4000	3,5
Auva LED1x6450 J011 T740 LSA2	525	205	102	6224	43,9	142	70+	4000	3,5
Auva LED1x7350 J012 T740 LSA2	525	205	102	7082	51,7	137	70+	4000	3,5
Auva LED1x5700 J013 T740 LSA2	525	250	102	5493	35,8	153	70+	4000	4,9
Auva LED1x6700 J014 T740 LSA2	525	250	102	6469	43,3	149	70+	4000	4,9
Auva LED1x7750 J015 T740 LSA2	525	250	102	7478	51,0	147	70+	4000	4,9
Auva LED1x8700 J016 T740 LSA2	525	250	102	8378	58,6	143	70+	4000	5
Auva LED1x9700 J017 T740 LSA2	525	250	102	9336	66,5	140	70+	4000	5
Auva LED1x11050 J018 T740 LSA2	525	250	102	10623	78,3	136	70+	4000	5
Auva LED1x7600 J019 T740 LSA2	625	288	102	7325	48,3	152	70+	4000	7,2
Auva LED1x8950 J020 T740 LSA2	625	288	102	8625	57,7	149	70+	4000	7,2
Auva LED1x10350 J021 T740 LSA2	625	288	102	9970	68,0	147	70+	4000	7,3
Auva LED1x11600 J022 T740 LSA2	625	288	102	11170	77,3	145	70+	4000	7,3
Auva LED1x12900 J023 T740 LSA2	625	288	102	12448	87,7	142	70+	4000	7,3
Auva LED1x14700 J024 T740 LSA2	625	288	102	14164	103,3	137	70+	4000	7,3
Auva LED1x11400 J025 T740 LSA2	625	288	102	10987	71,6	153	70+	4000	7,2
Auva LED1x13400 J026 T740 LSA2	625	288	102	12937	86,6	149	70+	4000	7,3
Auva LED1x15500 J027 T740 LSA2	625	288	102	14956	100,9	148	70+	4000	7,3
Auva LED1x17400 J028 T740 LSA2	625	288	102	16755	116,0	144	70+	4000	7,3
Auva LED1x19350 J029 T740 LSA2	625	288	102	18671	131,6	142	70+	4000	7,3
Auva LED1x15200 J031 T740 LSA2	776	320	102	14649	94,5	155	70+	4000	9,4
Auva LED1x17900 J032 T740 LSA2	776	320	102	17250	114,2	151	70+	4000	9,4
Auva LED1x20700 J033 T740 LSA2	776	320	102	19941	134,5	148	70+	4000	9,4
Auva LED1x23150 J034 T740 LSA2	776	320	102	22340	154,7	144	70+	4000	9,4
Auva LED1x25800 J035 T740 LSA2	776	320	102	24895	175,5	142	70+	4000	9,4
Auva LED1x1900 J001 T730 LS140	525	205	102	1882	12,5	151	70+	3000	3,5
Auva LED1x2250 J002 T730 LS140	525	205	102	2222	15,1	147	70+	3000	3,5
Auva LED1x2600 J003 T730 LS140	525	205	102	2572	17,2	150	70+	3000	3,5
Auva LED1x2900 J004 T730 LS140	525	205	102	2882	19,8	146	70+	3000	3,5
Auva LED1x3250 J005 T730 LS140	525	205	102	3212	22,2	145	70+	3000	3,5
Auva LED1x3700 J006 T730 LS140	525	205	102	3177	26,1	122	70+	3000	3,5
Auva LED1x3800 J007 T730 LS140	525	205	102	3765	23,9	158	70+	3000	3,5
Auva LED1x4500 J008 T730 LS140	525	205	102	4445	28,9	154	70+	3000	3,5
Auva LED1x5200 J009 T730 LS140	525	205	102	5144	33,6	153	70+	3000	3,5
Auva LED1x5800 J010 T730 LS140	525	205	102	5765	38,7	149	70+	3000	3,5
Auva LED1x6450 J011 T730 LS140	525	205	102	6424	43,9	146	70+	3000	3,5
Auva LED1x7350 J012 T730 LS140	525	205	102	6354	51,7	123	70+	3000	3,5
Auva LED1x5700 J013 T730 LS140	525	250	102	5647	35,8	158	70+	3000	4,9
Auva LED1x6700 J014 T730 LS140	525	250	102	6667	43,3	154	70+	3000	4,9
Auva LED1x7750 J015 T730 LS140	525	250	102	7716	51,0	151	70+	3000	4,9
Auva LED1x8700 J016 T730 LS140	525	250	102	8647	58,6	148	70+	3000	5
Auva LED1x9700 J017 T730 LS140	525	250	102	9636	66,5	145	70+	3000	5
Auva LED1x11050 J018 T730 LS140	525	250	102	9532	78,3	122	70+	3000	5
Auva LED1x7600 J019 T730 LS140	625	288	102	7530	48,3	156	70+	3000	7,2
Auva LED1x8950 J020 T730 LS140	625	288	102	8889	57,7	154	70+	3000	7,2
Auva LED1x10350 J021 T730 LS140	625	288	102	10288	68,0	151	70+	3000	7,3

Product	Length, mm	Width, mm	Height, mm	Luminaire output ¹ , lm	System power ² , W	System efficacy ³ , lm/W	CRI	CCT ⁴ , K	Weight, kg
Auva LED1x11600 J022 T730 LS140	625	288	102	11530	77,3	149	70+	3000	7,3
Auva LED1x12900 J023 T730 LS140	625	288	102	12848	87,7	146	70+	3000	7,3
Auva LED1x14700 J024 T730 LS140	625	288	102	14611	103,3	141	70+	3000	7,3
Auva LED1x11400 J025 T730 LS140	625	288	102	11294	71,6	158	70+	3000	7,2
Auva LED1x13400 J026 T730 LS140	625	288	102	13334	86,6	154	70+	3000	7,3
Auva LED1x15500 J027 T730 LS140	625	288	102	15431	100,9	153	70+	3000	7,3
Auva LED1x17400 J028 T730 LS140	625	288	102	17295	116,0	149	70+	3000	7,3
Auva LED1x19350 J029 T730 LS140	625	288	102	19271	131,6	146	70+	3000	7,3
Auva LED1x15200 J031 T730 LS140	776	320	102	15059	94,5	159	70+	3000	9,4
Auva LED1x17900 J032 T730 LS140	776	320	102	17778	114,2	156	70+	3000	9,4
Auva LED1x20700 J033 T730 LS140	776	320	102	20575	134,5	153	70+	3000	9,4
Auva LED1x23150 J034 T730 LS140	776	320	102	23060	154,7	149	70+	3000	9,4
Auva LED1x25800 J035 T730 LS140	776	320	102	25695	175,5	146	70+	3000	9,4
Auva LED1x1900 J001 T740 LS140	525	205	102	1940	12,5	155	70+	4000	3,5
Auva LED1x2250 J002 T740 LS140	525	205	102	2285	15,1	151	70+	4000	3,5
Auva LED1x2600 J003 T740 LS140	525	205	102	2641	17,2	154	70+	4000	3,5
Auva LED1x2900 J004 T740 LS140	525	205	102	2959	19,8	149	70+	4000	3,5
Auva LED1x3250 J005 T740 LS140	525	205	102	3297	22,2	149	70+	4000	3,5
Auva LED1x3700 J006 T740 LS140	525	205	102	3752	26,1	144	70+	4000	3,5
Auva LED1x3800 J007 T740 LS140	525	205	102	3880	23,9	162	70+	4000	3,5
Auva LED1x4500 J008 T740 LS140	525	205	102	4569	28,9	158	70+	4000	3,5
Auva LED1x5200 J009 T740 LS140	525	205	102	5282	33,6	157	70+	4000	3,5
Auva LED1x5800 J010 T740 LS140	525	205	102	5918	38,7	153	70+	4000	3,5
Auva LED1x6450 J011 T740 LS140	525	205	102	6594	43,9	150	70+	4000	3,5
Auva LED1x7350 J012 T740 LS140	525	205	102	7503	51,7	145	70+	4000	3,5
Auva LED1x5700 J013 T740 LS140	525	250	102	5820	35,8	163	70+	4000	4,9
Auva LED1x6700 J014 T740 LS140	525	250	102	6854	43,3	158	70+	4000	4,9
Auva LED1x7750 J015 T740 LS140	525	250	102	7923	51,0	155	70+	4000	4,9
Auva LED1x8700 J016 T740 LS140	525	250	102	8876	58,6	151	70+	4000	5
Auva LED1x9700 J017 T740 LS140	525	250	102	9891	66,5	149	70+	4000	5
Auva LED1x1050 J018 T740 LS140	525	250	102	11255	78,3	144	70+	4000	5
Auva LED1x7600 J019 T740 LS140	625	288	102	7761	48,3	161	70+	4000	7,2
Auva LED1x8950 J020 T740 LS140	625	288	102	9138	57,7	158	70+	4000	7,2
Auva LED1x10350 J021 T740 LS140	625	288	102	10564	68,0	155	70+	4000	7,3
Auva LED1x11600 J022 T740 LS140	625	288	102	11835	77,3	153	70+	4000	7,3
Auva LED1x12900 J023 T740 LS140	625	288	102	13189	87,7	150	70+	4000	7,3
Auva LED1x14700 J024 T740 LS140	625	288	102	15007	103,3	145	70+	4000	7,3
Auva LED1x11400 J025 T740 LS140	625	288	102	11641	71,6	163	70+	4000	7,2
Auva LED1x13400 J026 T740 LS140	625	288	102	13707	86,6	158	70+	4000	7,3
Auva LED1x15500 J027 T740 LS140	625	288	102	15846	100,9	157	70+	4000	7,3
Auva LED1x17400 J028 T740 LS140	625	288	102	17753	116,0	153	70+	4000	7,3
Auva LED1x19350 J029 T740 LS140	625	288	102	19783	131,6	150	70+	4000	7,3
Auva LED1x15200 J031 T740 LS140	776	320	102	15521	94,5	164	70+	4000	9,4
Auva LED1x17900 J032 T740 LS140	776	320	102	18277	114,2	160	70+	4000	9,4
Auva LED1x20700 J033 T740 LS140	776	320	102	21128	134,5	157	70+	4000	9,4
Auva LED1x23150 J034 T740 LS140	776	320	102	23670	154,7	153	70+	4000	9,4
Auva LED1x25800 J035 T740 LS140	776	320	102	26377	175,5	150	70+	4000	9,4

¹Tolerance range for optical and electrical data: ±10%. Values apply to an ambient temperature of 25°C. NORTHCLIFFE LIGHTING is constantly developing and improving its products. The right is reserved to change any product specifications without prior notification

²Photos are for illustrational purposes only. The exact appearance of the product may vary depending on the monitor settings, options selected and other factors.

Available options:

T730	Colour temperature 3000K, CRI 70+	LS140	Optics with 140° beam angle
T740	Colour temperature 4000K, CRI 70+	DALI	Driver with DALI interface
T750	Colour temperature 5000K, CRI 70+	CLO	Driver with Constant Light Output functionality
T757	Colour temperature 5700K, CRI 70+	ADIM	Driver with autonomous two-level dimming
T765	Colour temperature 6500K, CRI 70+	PCA	Photocell 20mm miniature type, IP65, 35 lux; 1:05 ratio
T830	Colour temperature 3000K, CRI 80+	DALI NEMA5p	Driver with DALI interface and integrated NEMA 5 pin socket. W/O sensor
T840	Colour temperature 4000K, CRI 80+	DALI ZHAGA18	Driver with D4i interface and integrated ZHAGA 18 socket. W/O sensor, up
T850	Colour temperature 5000K, CRI 80+	DALI ZHAGA18 DOWN	Driver with D4i interface and integrated ZHAGA 18 socket. W/O sensor, down
T857	Colour temperature 5700K, CRI 80+	DALI 2xZHAGA18	Driver with D4i interface and integrated two ZHAGA 18 sockets. W/O sensor, up&down
T865	Colour temperature 6500K, CRI 80+	II	Electric Shock protection class II
LSA1	Optics with asymmetric beam SA1, Area lighting with shorter illumination distances	CBF3x1.5-N m	Outgoing flexible cable 3x1.5mm ² . Cable length: according to the customer's specification
LSA2	Optics with asymmetric beam SA2, Narrow forward throw beam for area lighting	CBF5x1.5-N m	Outgoing flexible cable 5x1.5mm ² . Cable length: according to the customer's specification
LSM1	Optics with asymmetric beam SM1, universal road lighting	Tmin-40C	Luminaire suitable for low ambient temperatures up to -40 C
LSM2	Optics with asymmetric beam SM2, Fulfilling EN13201 M class requirements where road width is similar to pole height	*note - Tmin40C option is applicable for models J001...J012	
LSS1	Optics with asymmetric beam SS1, Fulfilling EN13201 M class requirements where road width is equal or less the pole height	10KV	Additional Surge Protection device - 10KV
LSS2	Optics with asymmetric beam SS2, Fulfilling EN13201 M class requirements for wider roads	ETC	External temperature control for protecting LED modules against overheating
LSPR	Fully asymmetric beam designed to highlight pedestrian crossings for right side traffic	RAL7022S	Dark grey, RAL7022S
LSPL	Fully asymmetric beam designed to highlight pedestrian crossings for left side traffic	RAL	RAL colour

Available accessories:



Product: WALL MTG bracket (Street LED D60mm 10° P7035S)
 Description: Bracket for street luminaire installation onto wall, pole diameter D60mm, 10 angle, light grey RAL7035S, 1pcs



Product: Power supply connector - IP66/IP68, 3x1.5mm2
 Description: Quick and easy to connect power supply and luminaire cables connector - IP66/IP68, 3x1.5mm2, 400V/16A, 1pcs



Product: Pole adapter RAL7035S (D60 into D76mm)
 Description: Console adapter from luminaire D60 to pole top D76 mm. Light grey, RAL7035S



Product: WALL MTG bracket (Street LED D60mm 10° P7022S)
 Description: Bracket for street luminaire installation onto wall, pole diameter D60mm, 10 angle, dark grey RAL7022S, 1pcs

